



# VAN3F32MS



JOB NAME: \_\_\_\_\_

DATE: \_\_\_\_\_

TYPE: \_\_\_\_\_

## DESCRIPTION

Sensor controlled Vandalproof fixtures. VAN 3 up to 42 watts CFL. VAN5 up to 96 watts CFL, VAN6 up to 26 watts CFL @ 120v. Sensor color matched to fixture. Sensor is not vandalproof. Lamps supplied.

## SPECIFICATIONS

### "No Hands" Auto Testing:

Auto mode starts after 4 minutes of testing.  
No adjustment needed.

### Built for Severe Conditions:

Double weatherproofing for long life

### LED Detection Indicator:

Glowes red day and night for "on-guard" deterrence.

### Manual Override:

Double flip wall switch logic prevents activation by short power outages. Resets after 8 hours. No extra wiring needed.

### Photocontrol:

Deactivates lights during daylight. Fully adjustable for 24 hour operation or custom applications. Please specify voltage.

### Quick Test Time:

5 seconds test time for fast installation.  
Works day or night.

### Sensor Case Construction:

Precision molded Lexan®

### Surge Protection:

Withstands up to 3000 volts

### Time Adjustment:

5 seconds to 15 minutes CFL lamps have longer life if Time Adjustment is set to < 7 minutes.

### UL Listing:

Suitable for wet locations.

### Vandal Resistant Lens:

Hard lens resists vandalism

### Voltage:

120 volts AC 60 Hz.

### Ballast Minimum Starting Temperature:

-22

### Min Start Temp

0°

### Patents:

RAB sensor and fixture designs are protected under U.S. and International Intellectual Property laws

### Color:

Bronze

### Weight:

7

## ORDERING INFORMATION

**Compact Fluorescent**  
Lamp supplied with fixture

| Total<br>Watts | Lamp<br>Type  | Lamp<br>Base | Ballast       | Starting Amps/ Operating Amps |      |      |      | Input<br>Watts | LAMP<br>ANSI | Initial<br>Lumens | Lamp<br>Hours |
|----------------|---------------|--------------|---------------|-------------------------------|------|------|------|----------------|--------------|-------------------|---------------|
|                |               |              |               | 120V                          | 208V | 240V | 277V |                |              |                   |               |
| 32             | 32w<br>Triple | GX24q-3      | Electronic QT | 0.31                          | 0.2  | 0.2  | 0.13 | 32             |              | 2400              | 12000         |

### Factory Installed Options

Add suffix to Catalog Number

Note: Specifications may change without notice

**RAB Lighting, Inc.** • 170 Ludlow Ave • Northvale, NJ 07647 • Tel: 888 RAB-1000 • Fax: 888 RAB-1232 • [www.rabweb.com](http://www.rabweb.com)  
© 2009