

Maestro Wireless Dimmers

Maestro Wireless dimmers function much like standard dimmers, but can be controlled from Pico™ wireless controls and Lutron® Radio Powr Savr™ sensors. Local lighting controls are useful in locations where single circuits of lighting need to be dimmed or switched.

Maestro Wireless dimmers incorporate advanced features such as fade on/fade off, long fade off, and rapid full on.

Maestro Wireless local controls include a Front Accessible Service Switch (FASS™) for safe lamp replacement. Maestro Wireless controls install in single-pole or multi-location applications.

Model Numbers

Dimmers

Halogen/Incandescent/Magnetic Low-voltage

MRF2-600M-XX	600 W Incandescent Dimmer 120 V~
MRF2-6MLV-XX	600 W/600 VA Incandescent/MLV Dimmer 120 V~
MRF2-6ND-120-XX*	600 W/600 VA Spec Grade Neutral wire Dimmer 120 V~
MRF2-10D-120-XX	1000 W/1000 VA Spec Grade Dimmer 120 V~

3-wire Fluorescent

MRF2-F6AN-DV-XX*	6 A 3-wire Fluorescent Spec Grade Neutral wire Dimmer 120-277 V~
------------------	--

Electronic Low-Voltage Dimmer—

Available July 2010

MRF2-6ELV-120-XX*	600 W ELV Dimmer 120 V~ Neutral optional
-------------------	--

* NEUTRAL WIRE REQUIRED.

Dimmer



Companion Dimmer



Companion Controls

Claro® Gloss Finishes

MA-R-XX	Companion Dimmer 120 V~
MA-R-277-XX	Companion Dimmer 277 V~

Satin Colors® Satin Finishes

MSC-AD-XX	Companion Dimmer 120 V~
MSC-AD-277-XX	Companion Dimmer 277 V~

“XX” in the model number represents color/finish code.

Job Name:	Model Numbers:
Job Number:	