

# **SMS500**



JOB NAME:	
DATE:	
TYPE:	

#### **DESCRIPTION**

Wall or ceiling mount to control 500 watts Incandescent or 100 watts Fluorescent lighting. Vandalproof lens. Full 180• view. Cover not included.

# **SPECIFICATIONS**

#### "No Hands" Auto Testing:

Auto mode starts after 4 minutes of testing. No adjustment needed.

# Adjustments:

Time, ambient light & sensitivity

#### **Ambient Light Sensing:**

Adjustable

### Compatibility:

Compatible with most electronic ballasts. Not compatible with instant start ballasts.

#### **Detection:**

180• detection pattern

# **Fluorescent Watts Switched:**

250 watts @ 120 volts

#### **Incandescent Watts Switched:**

500 watts @ 120 volts

# **LED Detection Indicator:**

LED glows red day & night for "on guard" deterrence.

# **Manual Override:**

Double flip wall switch logic prevents activation by brief power outages. Resets after 8 hours. No extra wiring needed.

#### **Manual Switch:**

None

# Patents:

RAB sensor and fixture designs are protected under U.S. and International Intellectual Property laws.

# **Power Consumption:**

Negligible

#### **Photoelectric Control:**

Deactivates lights during daylight. Fully adjustable for 24 hour operation or custom applications.

#### **Quick Test Time:**

5 second test time for fast installation. Works day or night.

### RF Immunity:

Circuits fully shielded for maximum radio frequency immunity.

### Ratings:

5 amps

# **Surge Protection:**

Withstands up to 3000 volts

# **Switching Capacity:**

Relay On/Off Model: Switches 240 watts when lights are mounted to sensor. 500 watts Incandescent or 240 watts Fluorescent of remotely mounted lighting @ 120 volts

# Time Adjustment:

5 seconds to 15 minutes

#### Time Delay:

5 seconds to 15 minutes

#### **UL Listing:**

Suitable for wet locations.

# Voltage:

120 volts AC 60 Hz.

#### Warranty:

5 year sensor warranty

# Color:

Bronze

# Weight:

0.5

# **DIMENSIONS**



# **DETECTION PATTERN**

