

## **BARBECUE LIGHTS BQ-03-FC,-FD-SERIES**

## **SPECIFICATIONS**

CONSTRUCTION: Heavy-duty spun aluminum bell (BQ-03-FC) mounted to 24" or 36" (designated -36) stainless steel flex arm, chrome plated with black polyolefin shrink cover

CLAMP: 5" heavy duty stainless steel C-clamp with 6" black plastic T-handle

SWITCH: On/off push button control with rubber boot cover

WIRING: 12v. models: 18/2 black zip cord, 9 foot length from base of fixture, 120v. models: 1 foot black SJT-WA grounded power cord supplied

CONNECTION: Optional FA-05 Quick Connector required to attach fixture lead to main cable of landscape lighting system. (12 volt only)

SOCKET: Brass nickel plated screw shell with high-temperature ceramic contact and stainless steel spring (Ba15s) 200°C silicone lead wires

LAMP LIFE: 2000 hours average rating

STANDARD FINISH: Black texture polyester powder coat. With powder coat options, fixture heads will have black shrink tubing over flex arms, clamp will have black finish-optional finishes available

CONSTRUCTION: Spun aluminum bell (BQ-03-FD) mounted to 24" or 36" (designated -36) stainless steel flex arm, chrome plated with black polyolefin shrink cover.

BASE AND SWITCH: New style stainless steel base with on/off push button control with rubber boot cover

WIRING: 12v. models: 18/2 black zip cord, 7 foot length from base of fixture

**SOCKET:** Brass nickel plated screw shell with ceramic contact and stainless steel spring (Ba15s) 200°C silicone lead wires

CONNECTION: Optional FA-05 Quick Connector required to attach fixture lead to main cable of landscape lighting system. (12 volt only)

LAMP LIFE: 2000 hours average rating

**STANDARD fINISH:** Black texture polyester powder coat–optional finishes available


## ORDERING INFORMATION


CATALOG NO.	DESCRIPTION	ARM LENGTH	LAMP SUPPLIED	STANDARD FINISH
12 VOLT				
Transformer required for	all low-voltage BBQ lights.			
BQ-03-FC	4.5" dia. heavy-duty spun alum. b	ell 24"	20 watt T4	Black texture
BQ-03-FC-SS	4.5" dia. heavy-duty spun stainles steel bell	ss 24"	20 watt T4	Stainless steel
BQ-03-FC-36	4.5" dia. heavy-duty spun alum. b	ell 36"	20 watt T4	Black texture
BQ-03-FC-36-SS	4.5" dia. heavy-duty spun stainles steel bell		20 watt T4	Stainless steel
BQ-03-FD	4.5" dia. heavy-duty spun alum. b	ell 24"	20 watt T4	Black texture
BQ-03-FD-SS	4.5" dia. heavy-duty spun stainles steel bell	ss 24"	20 watt T4	Stainless steel
BQ-03-FD-36	4.5" dia. heavy-duty spun alum. b	ell 36"	20 watt T4	Black texture
BQ-03-FD-36-SS	4.5" dia. heavy-duty spun stainles steel bell	ss 36"	20 watt T4	Stainless steel
120 VOLT				
9 foot black SJT-WA grou	nded power cord supplied with all 1	120v. Flex Clamp	(-FC) fixtures.	
BQ-03-FC-120V	4.5" dia. heavy-duty spun alum. b	ell 24"	35 watt T4	Black texture
BQ-03-FC-120V-SS	4.5" dia. heavy-duty spun stainles steel bell	ss 24"	35 watt T4	Stainless steel
BQ-03-FC-120V-36	4.5" dia. heavy-duty spun alum. b	ell 36"	35 watt T4	Black texture
BQ-03-FC-120V-36-SS	4.5" dia. heavy-duty spun stainles		35 watt T4	Stainless steel



8Q-03-FC-120V-36 8Q-03-FC-120V-36-SS	4.5" dia. heavy-duty spun alum. bell 4.5" dia. heavy-duty spun stainless	36" 36"	35 watt T4 35 watt T4	Black texture Stainless steel
tandard wiring black whi	steel bell te and ground with 9" leads			
tandara wining black, win	ic and ground with 5 icads			
Q-03-FD-120V	4.5" dia. heavy-duty spun alum. bell	24"	35 watt T4	Black texture
8Q-03-FD-120V-SS	4.5" dia. heavy-duty spun stainless steel bell	24"	35 watt T4	Stainless steel
Q-03-FD-120V-36	4.5" dia. heavy-duty spun alum. bell	36"	35 watt T4	Black texture
8Q-03-FD-120V-36-SS	4.5" dia. heavy-duty spun stainless steel bell	36"	35 watt T4	Stainless steel







JOB INFORMATION

Job Name:

Cat. No.:

Note: Drawing of fixtures shown with arm extended upward to illustrate length only. Hat must be pointed downwards for proper operation.

CATER TER	TEA
(5)	) Us

Lamp(s).	
Specifier:	
Contractor:	
Notes:	
FOCUS INDUSTRIES INC. 25301 COMMERCENTRE DRIVE	www.focusindustries.com sales@focusindustries.com (949) 830-1350 • FAX (949) 830-3390

12v. fixtures: 25 foot 16/2 fixture lead wire available; add -25F to catalog number. For use with Focus CPC or hub supplied by others.

FSA-00

В B

В

В

Powder Coat Finishes	Black Texture (Standard)	Antique Verde	Bronze Texture	Camel	White Texture	Hunter Texture	Rust	Weathered Iron	Weathered Brown	Stucco	Rubbed Verde	Chrome Powder	Terra Cotta
Ordering Code	-BLT	-ATV	-BRT	-CAM	-WTX	-HTX	-RST	-WIR	-WBR	-STU	-RBV	-CPR	-TRC