

JOB NAME:	
DATE:	
TVPE:	

# **DESCRIPTION**

Fully shielded, Full Cutoff Wallpack for higher wattages! Full Cutoff optics with flat tempered glass lens. EZ mount knockouts for easy wiring. Lamp supplied.

# **SPECIFICATIONS**

#### Finish

Chip and fade resistant polyester powder coating.

#### Housing:

Die cast aluminum, 1/2" NPS tapped top, both sides and back for conduit or photocontrol. Hinged refractor. Continuous one piece silicone rubber gasket.

### Reflector:

Semi-Specular anodized aluminum, removable for installation. Symmetrical light pattern maximizes distance between

#### fixtures UL Listing:

Suitable for wet locations. HID fixtures can be wired with 90° C supply wiring if supply wires are routed 3" away from the ballast. Knockouts for easy wall box mounting

# **Conduit Openings:**

Top, side, back and bottom

#### Patents:

Pat. D561.377

### **Photocontrol:**

Button Photocontrol installed and wired for 120V

# Quad Tap:

Fixture works with 120, 208, 240, and 277 volts


### Color:

Bronze


# Weight:

11.15

# **DIMENSIONS**



### **PHOTOMETRIC**



Mounti Height	ng Multiplier
8'	1.6
10'	1.0
12'	.7
16'	.4
20'	.25

Watts	CFL		
100	1.5		<u> </u>
70	1.0	.9	
50	.6	.5	
35	.4	.5	
42			.5

# ORDERING INFORMATION

**High Pressure Sodium** Total Lamp Lamp Starting Amps/ Operating Amps Input LAMP Initial Lamp **Ballast** 120V 208V 240V Lamp supplied with fixture Watts Type Base Hours ED17 Medium HX-HPF QT .8/.9 .5/.5 S62 6400 24000

Factory Installed Options Tamperproof screws (/TP)
Add suffix to Catalog Number Swivel Photocontrol (/PCS)

Single fusing for 120 and 277 volt (/F)

Button Photocontrol wired for 208 - 277 volt (/PC2)

Button Photocontrol (/PC)

Note: Specifications may change without notice