

JOB NAME:	
DATE:	
TVDE:	

## **DESCRIPTION**

Fully shielded, Full Cutoff Wallpack for higher wattages! Full Cutoff optics with flat tempered glass lens. EZ mount knockouts for easy wiring. Lamp supplied.

# **SPECIFICATIONS**

Chip and fade resistant polyester powder coating.

#### Housing:

Die cast aluminum, 1/2" NPS tapped top, both sides and back for conduit or photocontrol. Hinged refractor. Continuous one piece silicone rubber gasket.

#### Reflector:

Semi-Specular anodized aluminum, removable for installation. Symmetrical light pattern maximizes distance between

# fixtures UL Listing:

Suitable for wet locations. HID fixtures can be wired with 90° C supply wiring if supply wires are routed 3" away from the ballast.

Knockouts for easy wall box mounting

#### **Conduit Openings:**

Top, side, back and bottom

#### Patents:

Pat. D561,377

# **Photocontrol:**

/PC2 = 277V

# Quad Tap:

Fixture works with 120, 208, 240, and 277 volts


#### Color:

Bronze


# Weight:

11.15

# **DIMENSIONS**



#### **PHOTOMETRIC**



	manapiee
Mounti Height	ng Multiplier
8'	1.6
10'	1.0
12'	.7
16'	.4
20'	.25

Watts	CFL		
100	1.5		<u> </u>
70	1.0	.9	
50	.6	.5	
35	.4	.5	
42			.5

## ORDERING INFORMATION

**High Pressure Sodium** Total Lamp Lamp Starting Amps/ Operating Amps Input LAMP Initial Lamp **Ballast** 120V 208V 240V Lamp supplied with fixture Watts Type Base Hours ED17 Medium HX-HPF QT .8/.9 .5/.5 6400 24000

**Factory Installed Options** Tamperproof screws (/TP) Add suffix to Catalog Number Swivel Photocontrol (/PCS)

Single fusing for 120 and 277 volt (/F)

Button Photocontrol wired for 208 - 277 volt (/PC2)

Button Photocontrol (/PC)

Note: Specifications may change without notice