



| JOB NAME: |
|-----------|
| DATE:     |
| TYPE:     |

## DESCRIPTION

Fully shielded, Full Cutoff Wallpack for higher wattages! Full Cutoff optics with flat tempered glass lens. EZ mount knockouts for easy wiring. Lamp supplied.

## **SPECIFICATIONS**

### Finish:

Chip and fade resistant polyester powder coating.

### Housing:

Die cast aluminum, 1/2" NPS tapped top, both sides and back for conduit or photocontrol. Hinged refractor. Continuous one piece silicone rubber gasket.

### **Reflector:**

Semi-Specular anodized aluminum, removable for installation. Symmetrical light pattern maximizes distance between

#### fixtures. UL Listing:


Suitable for wet locations. HID fixtures can be wired with 90° C supply wiring if supply wires are routed 3" away from the ballast.

# Conduit Openings:


Top, side, back and bottom **Cradle:** Capacitor cradle for better heat absorption. **Mounting:** Knockouts for easy wall box mounting **Patents:** Pat. D561,377 **Photocontrol:** Button Photocontrol installed and wired for 120V

Color: Bronze Weight: 9.07

### DIMENSIONS



## PHOTOMETRIC



## ORDERING INFORMATION

| High Pressure Sodium<br>Lamp supplied with fixture        | Total<br>Watts  | Lamp<br>Type | Lamp<br>Base | Ballast  | Startin<br>120V | g Amps/ C<br>208V | Dperating 240V | Amps<br>277V | Input<br>Watts | LAMP<br>ANSI | Initial<br>Lumens | Lamp<br>Hours |
|---|---|--------------|--------------|--|-----------------|-------------------|----------------|--------------|----------------|--------------|-------------------|---------------|
|   | 70  | ED17         | Medium       | R-HPF 120V   | .9/.8           |                   |                |              | 86             | S62          | 6400              | 24000         |
| Factory Installed Options<br>Add suffix to Catalog Number | Tamperproof screws (/TP)<br>Swivel Photocontrol (/PCS)<br>Single fusing for 120 and 277 volt (/F) |              |              | Button Photocontrol wired for 208 - 277 volt (/PC2)<br>Button Photocontrol (/PC) |                 |                   |                |              |                |              |                   |               |

Note: Specifications may change without notice

**RAB Lighting, Inc.** • 170 Ludlow Ave• Northvale, NJ 07647 • Tel: 888 RAB-1000 • Fax: 888 RAB-1232 • www.rabweb.com