

# WP2CSN150/PC



JOB NAME:	
DATE:	
TVDE:	

## **DESCRIPTION**

Wallpack with cutoff glare shield. All aluminum precision die cast construction with tempered glass lens. 30° cutoff strip included. Lamp supplied.

## **SPECIFICATIONS**

## **Cutoff Lens:**

Tempered glass.

## Finish:

Chip and fade resistant polyester powder coating.

## Housing:

Die cast aluminum, 1/2" NPS tapped holes top, both sides and back for conduit or photocontrol. Hinged refractor frame. Continuous silicone rubber gasket.

#### Reflector:

Specular anodized aluminum, removable for installation. Symmetrical light pattern maximizes distance between fixtures.

## Photocell:

Button Photocell installed and wired for 120V

#### Refractor:

Prismatic optics designed to minimize glare and throw light down and out. Heat resistant borosilicate glass.

## **UL Listing:**

Suitable for wet locations. HID fixtures can be wired with 90° C supply wiring if supply wires are routed 3" away from ballast.

#### Patents:

RAB sensor and fixture designs are protected under U.S. and International Intellectual Property laws


### Color:

**Bronze** 


## Weight:

13.8

# **DIMENSIONS**



## **PHOTOMETRIC**



Multiples of Mounting Height								
Mounting Height Multiplier			Watts	Multi HPS	plier MH	CFL		
8'	1.6		175		1.0			
10'	1.0		150	1.1	.9			
12'	.7		100	.6	.6			
16'	.4		70	.4	.4			
20'	.25		42			.2		

## ORDERING INFORMATION

 High Pressure Sodium
 Total
 Lamp
 Lamp

 Lamp supplied with fixture
 Watts
 Type
 Base
 Ballast

 150
 ED17
 Medium
 R-NPF 120V

 Starting Amps/ Operating Amps
 Input Watts
 LAMP Lamp Hours
 Lamp Hours

 4.5/3.2
 170
 S55
 16000
 24000

Factory Installed Options Add suffix to Catalog Number Tamperproof screws (/TP)
Swivel Photocontrol (/PCS)
Single fusing for 120 and 277 volt (/F)

Double fusing for 208 and 240 volt (/FF) Button Photocontrol for 208 - 277 volt (/PC2) Button Photocontrol (/PC)

Note: Specifications may change without notice

RAB Lighting, Inc. • 170 Ludlow Ave• Northvale, NJ 07647 • Tel: 888 RAB-1000 • Fax: 888 RAB-1232 • www.rabweb.com © 2010 RAB Lighting, Inc.