# Description

The HALO Home Smart Plug-In Lamp Dimmer enables convenient control for standard floor and table lamps using the HALO Home mobile app. Combine with more HALO Home light fixtures and accessories to create groups and scenes throughout the home. Smart Plug-In Lamp Dimmer is for lamps only.

# HALO HOME

Catalog #	Туре
	_
Project	
Comments	Date
Prepared by	

## **Specification Features**

#### Features

- Manual ON/OFF and brightness control with the side panel push button
- Using the HALO Home app with the Lamp Dimmer you can program the following controls:
- On/Off
- Dimming
- Groups
- Scheduling
- Scenes
- · Scenes

# Driver

- Grounded 3-wire power connection for safety
- Power: 120VAC, 60Hz
- For use with 110/120V compatible sockets

#### **Compatible Products**

- 2.5A; 300W Incandescent or 150W Dimmable CFL/LED
- Maximum load for the Bluetoothcontrolled outlet: 2.5A, 300W Incandescent or 150W Dimmable CFL/LED.

#### **Factory Reset**

- Hold the ON button for more than
  15 seconds
- Constant flashing of blue status indicator light indicates successful reset.

#### Compliance

- cULus certified EMI/RFI emissions per FCC
- 47CFR Part 15 consumer limits Operating Temperature Range:

# -30 C to +45C Warranty

Five year limited warranty, consult website for details. eaton.com/lighting/legal





# HALO Home HWP1

Smart Plug-In Lamp Dimmer

Lamps Only

#### Dimensions





# **Ordering Information**

#### SAMPLE NUMBER: HWP1BLE40AWH

HWP1 = Smart Plug-In Lamp Dimmer	BLE40A=Bluetooth wireless mesh 4.0 control	WH=White
Device	Driver	Finish







Specifications and dimensions subject to change without notice.