

## E26 6" Trim Series


### DESCRIPTION

Gimbal with 25° tilt (max.) and self-flange in the 6" trim family for use in recessed downlighting. Compatible for use in Halo and other housings.

Catalog #		Type
Project		
Comments		Date
Prepared by		

### SPECIFICATION FEATURES

- 25° Tilt (max.), 360° rotation
- Adjustable gimbal for PAR38 lamps
- Torsion spring retention
- Socket supporting gimbal
- Self-flanged trim ring sized to hide gaps caused by construction tolerances.



#### Dimensions:


A: 4-1/2" [113mm]  
H: 1-1/8" [29mm]  
OD: 7-3/4" [197mm]

Housings		Max Lamp Compatibility
H7ICT	H7RICT	
H7ICAT	H7RICAT	45W PAR38
E7ICAT	E7RICAT	
H7ICTNB		
H7ICATNB		45W PAR38L
E7ICATNB		
H7T	E7TAT	90W PAR38
H7TCP		
H7RT	E7RTAT	
H7TNB	E7TATNB	90W PAR38

Compatible with Halogen, Incandescent, LED\* or CFL\* lamps.




**6170WH**  
White Gimbal



**6170BK**  
Black Gimbal



**6170SN**  
Satin Nickel Gimbal



**6170TBZ**  
Tuscan Bronze Gimbal

### ORDERING INFORMATION

SAMPLE NUMBER: 6170WH

Trim	Finish
6170= 6" Gimbal with 25° tilt (max.), Self-flange	<b>WH</b> =White <b>BK</b> =Black <b>SN</b> =Satin Nickel <b>TBZ</b> =Tuscan Bronze

### HALO HOUSING COMPATIBILITY

Trim #	Style	H7ICT	H7ICAT	H7RICT	H7RICAT	E7ICAT	E7RICAT	H7UICAT	H7ICTNB
6170	Adjustable	•	•	•	•	•	•	•	•
		H7ICATNB	E7ICATNB	H27ICAT	H27RICAT	E27ICAT	E27RICAT		
		•	•	—	—	—	—		
		H7T	H7TCP	H7RT	E7TAT	E7RTAT	H7TNB	E7TATNB	H27T
		•	•	•	•	•	•	•	—
		H27RT	E27TAT	E27RTAT					
		—	—	—					

For use in select other's housings, refer to U.L. classification list at [www.eaton.com/lighting/legal](http://www.eaton.com/lighting/legal).

\*UL1993 listed LED & CFL equivalent lamps permitted. Consult lamp manufacturer for conditions of use. Eaton does not warranty the lamp.