
FEATURES

- Designed for concise control of each circuit
- Provides two separate 20 Amp circuits
- Track comes in 4', 8' and 12' lengths
- Structural channel is extruded aluminum
- Finishes: White (P) and Black (MB)

Compliances may not apply to all product configurations. Please consult the product spec sheet for compliance details. COMPLIANCES: UL/cUL Listed, CSA Listed







TRACK SYSTEMS - TWO CIRCUIT

TWO-CIRCUIT **POWER-TRAC**

ORDERING INFORMATION

SAMPLE NUMBER: | 641P

Track	Finishes	Connectors (Order Separately)	Accessories	Current Limiters (Order Separately)	
.641 =4' Halo-2 Two Circuit Track .642 =8' Halo-2 Two Circuit Track .643 =12' Halo-2 Two Circuit Track	MB=Black P=White	L900=Outlet Box Cover L941=Live End Connector L942=Flexible Connector L943=Straight/*L* Connector L945E=Left "T* Connector L946F=T&T* Connector L946="X* Connector L946="X* Connector L949=Winii Joiner L980=Live End Conduit Adapter L980=Live End Conduit Adapter L980=Conduit Continuation Kit Finishes MB=Black P=White	DE641=Dead End L18=18" Steel Stem L36=36" Steel Stem L48=48" Steel Stem L951=Wire Way Cover for Pendant Assembly Kit L983=T-Bar Attachment Clip L992=Pendant Kit assembly L994=Pendant Adapter <u>Finishes</u> MB=Black P=White	Current Limiter-Center Feed LC943=LC943 Circuit 1 Breaker *CB1=Circuit 1 Breaker LC943CB1200=1200W (10A @ 120V) Circuit 2 Breaker LC943CB120=120W (1A @ 120V) LC943CB120=120W (1A @ 120V) LC943CB300=300W (25A @ 120V) LC943CB600=600W (5A @ 120V) LC943CB960=960W (8A @ 120V)	Current Limiter-End Feed Circuit 1 Breaker *CB1=Circuit 1 Breaker LC941CB120=120W (1A @ 120V) Circuit 2 Breaker *CB2=Circuit 2 Breaker *CB2=Circuit 2 Breaker LC941CB1200=1200W (10A @ 120V) LC941CB300=300W (5A @ 120V) LC941CB300=300W (5A @ 120V) LC941CB300=960W (8A @ 120V) Finishes MB=Black P=White

CONNECTORS AND ACCESSORIES



L900 Outlet Box Cover

L929 Floating Canopy and Connector



L941 Live End Connector L942 Flex Joiner



L943 Straight/L Connector



L945R Right T Connector



L945L Left T Connector



L946 X Connector

Assembly





DE641 Dead End





L994 45° Pendant Adapter



Pendant Assembly Kit



L983 T-Bar Attachment Clip



LC941 Current Limiter



L989 Conduit Continuation Kit

HALO

Specifications and dimensions subject to change without notice. Consult your Cooper Lighting Solutions Representative or visit www.cooperlighting.com for available options, accessories and ordering information.