JUNO2INCH-DIM

<b>JUNO</b> °	
Project:	
Fixture Type:	
Location:	
Contact/Phone:	

# 600 LUMEN LED DIMMER COMPATIBILITY

FOR USE WITH: **2" LED SERIES** 

#### **DIMMER COMPATIBILITY**

#### **DEDICATED 120V ONLY HOUSING**

## Incandescent and Magnetic Low Voltage - Forward Phase Dimming

• Dimmable with the use of most forward phase dimmers • Dimming range is typically 100% down to 5% or lower with a minimum load of one fixture and a maximum load of 50% of the dimmer rated load (see example); both dimming range and maximum rated load may vary depending on dimmer model.

Example: Fixture Rating = 10W
Dimmer Rating = 600W

Equivalent Incandescent Load (EIL) Factor = 50% (.5)

(600/10) X .5 = 30 Fixtures per Dimmer

#### Juno Qualified Dimmers Include:

#### **Lutron® Model Numbers:**

- Glyder® GLV-600 Series\*
- Diva® DV/DVCL/DVLV Series\*
- Ariadni® AY/AYCL Series
   Skylark® S/SLV Series\*
- Skylark® Contour CTCL Series
- Toggler® TGCL Series
- Ceana® CNLV Series
- Nova T☆® NTLV Series
- Lumea® LGCL Series

#### Leviton® Model Numbers:

- IllumaTech™ IP106 Series\*
- SureSlide 6613

#### Whole House Integrated Control Systems:

• Lutron® Homeworks® QS HQRD-6D\* • Lutron® Grafik Eye® QS QSGRJ

• Lutron® Radio RA2® RRD-6D\*

#### **Electronic Low Voltage - Reverse Phase Dimming**

• Dimmable with the use of most electronic low voltage dimmers • Electronic low voltage dimmers require a neutral wire in the wall box • Dimming range is typically 100% down to 5% or lower with a minimum load of one fixture and a maximum load of 75% of the dimmer rated load (see example); both dimming range and maximum rated load may vary depending on dimmer model.

Example: Fixture Rating = 10W
Dimmer Rating = 600W

Equivalent Incandescent Load (EIL) Factor = 75% (.75)

(600/10) X .75 = 45 Fixtures per Dimmer

# Juno Qualified Dimmers include:

#### **Lutron® Model Numbers:**

- Nova T☆® NTELV Series\*
- Diva® DVELV Series\*
- Faedra® FAELV Series
- Skylark<sup>®</sup> SELV Series
- Maestro® MAELV Series\*
- Spacer System® SPSELV Series

#### Leviton® Model Numbers:

- IllumaTech™ IPEO4 Series
- VIZIA +® VPEO6-1LX Series

#### Whole House Integrated Control Systems:

- Lutron® Homeworks® QS HQRD-6NA Lutron® Radio RA2® RRD-6NA
- Lutron® Homeworks® LP-RPM-4A\* Lutron® Grafik Eye® QS QSGRJ PHPM-PA

Consult technical services for additional information regarding other dimmer model qualification.

Recommend using electronic low voltage dimmers for best overall performance. Dimmer compatibility is based on laboratory testing and dimming performance may vary in the field due to a variety of factors. The inclusion of a dimmer on this list is not a guarantee or warranty of compatibility. Dimmers not included on this list do not represent unacceptability, but rather just an indication they have not been evaluated. Refer to dimmer manufacturers for additional information regarding compatibility and performance.



<sup>\*</sup> Juno recommended dimmers

JUNO2INCH-DIM

# **600 LUMEN LED DIMMER COMPATIBILITY**

FOR USE WITH: 2" LED SERIES

#### **DIMMER COMPATIBILITY**

#### **UNIVERSAL VOLTAGE (120-277V) HOUSINGS**

### **0-10V Dimming Control**

• Dimming range of 100% down to 10% or lower with a minimum load of one fixture.

#### Juno Qualified Dimmers Include:

#### **Lutron® Model Numbers:**

- Nova® NFTV Series¹
- Nova T☆® NTFTV Series¹
- Diva® DVTV Series¹

#### **Leviton® Model Numbers:**

• IllumaTech™ IP710-DLX Series

1 Additional Lutron products required for switching functionality when using Lutron 0-10V dimmers (such as PP-20)

#### **Whole House Integrated Control Systems:**

- Lutron® Homeworks® GRX-TVMZ
  Lutron® Grafik Eye® QS GRX-TVI

Consult technical services for additional information regarding other dimmer model qualification.



<sup>\*</sup>Juno recommended dimmers