



# Junction Box - JBR32 Installation Instructions

WARNING: Fixtures must be grounded in accordance with local codes or the National Electrical Code. Portable spear or tree mounts using a cord and plug must be plugged into a receptacle protected by a Ground Fault Circuit Interrupter (GFCI) in accordance with the National Electrical Code. Failure to take these steps may result is serious personal injury. All electrical work should be done by a qualified electrician.

KEEP THIS SHEET FOR FUTURE REFERENCE.


**Tools Required:** □ Flat Blade Screwdriver

- 7/16" Open End or Socket
- □ RTV Sealant □ Thread Sealant

□ <sup>3</sup>⁄16" Hex Wrench

## Installation Instructions:


Make certain the electrical supply is **OFF** before installing equipment.



 Install plugs (provided) in bottom of junction box with thread sealant. Attach support stakes to side of junction box with bolts provided.



 Push junction box into ground. Keep level as it is being inserted. Dig a hole if soil conditions make installation difficult.




3. Attach fixture to junction box cover. Plan for fixture orientation and tighten locking screw. Connect wires observing polarity, i.e., green -to-ground, white-to-common, and black-to-voltage.



4. **IMPORTANT:** Wrap connections with dielectric compound (provided) to seal.



 Clean gasket surface before attaching gasket and cover. Check for final level. Adjust as necessary. Plug cord into a receptacle protected by a Ground Fault Circuit Interrupter (GFIC).



### KIM LIGHTING LIMITED WARRANTY

When installed in accordance with Kim Installation Instructions and accepted trade practices, the following shall apply:

#### **General Product Limited Warranty Coverage**

All material and component parts used in the manufacture of Kim Products, are warranted to be free from defects of material and/or workmanship for a period of 1 year from date of sale, with the following exceptions:

#### **Auxiliary Equipment:**

All auxiliary equipment (such as lamps, ballasts, and transformers) provided by and/or included in Kim Products shall carry the components manufacturer's warranty.

#### Copper, Bronze and Brass Landscape Components

Copper and Bronze Landscape fixture components shall be warranted against defects of material and/or workmanship, and failure due to corrosion, for a period of 25 years from date of sale.

Kim Lighting's brass components are constructed from several brass parts that are manufactured by various methods at various times. Since brass naturally deepens in color as it ages through the normal oxidation process, these parts may exhibit subtle differences in coloration when the product is new. This is normal and expected. These color differences will be eliminated shortly after installation through the normal brass oxidation process.

#### **Composite In-Grade Components**

Composite In-Grade fixture components installed below grade, shall be warranted against defects of material and/or workmanship, and failure due to corrosion, for a period of 7 years from date of sale.

#### Aluminum Landscape Components

Aluminum Landscape fixture components not in direct contact with soil, shall be warranted against defects of material and/or workmanship for a period of 3 years from date of sale. Aluminum fixture components in direct contact with soil shall be warranted from defects of material and failure from corrosion for a period of 1 year from date of sale.

#### Limit of Liability and General Conditions

Only products which are installed, used and maintained in accordance with applicable Kim instructions, specifications and accepted trade practices, are covered by the Kim Warranty. During the warranty period, with proof of purchase, Kim will repair or replace with the same or similar product, at Kim's option without charge. Labor costs are the owner's responsibility and are excluded from this warranty. This warranty is void if the product is modified, tampered with, misapplied, poorly installed, improperly maintained, or subjected to abnormal conditions.

Repair or replacement as provided under this warranty is the exclusive remedy of the purchaser. This warranty is in lieu of all other warranties, expressed, or implied, including any implied warranty of fitness for a particular application. Kim Lighting shall not be liable to the purchaser for indirect or consequential damages.



How may we serve you better? Please let us know. Visit our web site at: www.kimlighting.com Your concerns are important to us.