# LIGHTSAVER® ENCLOSURES

LS-E8 / LS-E12



#### **DESCRIPTION**

LightSaver Enclosures are suitable for use in housing the ELCU-100 Emergency Lighting Control Unit, or any other devices that can be DIN rail mounted. Rated NEMA 1, they are suitable for dry indoor locations, such as electrical rooms or closets.

#### **APPLICATIONS**


Available in two sizes, the enclosures feature screw covers. The 8"  $\times$  8" sized enclosure contains a single pre-mounted DIN rail suitable for holding up to 2 ELCU-100 modules. The larger enclosure is 12"  $\times$  12", and contains two rows of pre-mounted DIN rail. It can house up to 6 ELCU-100 modules

## **SPECIFICATIONS**

- NEMA 1 rated for dry indoor locations
- Surface mount
- Single pre-mounted DIN rail in 8" x 8" size;
  Dual pre-mounted DIN rail in 12" x 12" size
- Dimensions: 8" x 8" x 4" (203.2mm x 203.2mm x 101.6mm) or 12" x 12" x 4" (304.8mm x 304.8mm x 101.6mm) LxWxD


### **ENCLOSURE EXAMPLES**

LS-E8



Includes one DIN rail for mounting up to 2 ELCU-100s

LS-E12



Includes two rows of DIN rail for mounting up to 6 ELCU-100s

## ORDERING INFORMATION

Ca	talog #	Description	Dimensions	
	LS-E8	Screw Cover Enclosure	8" x 8" x 4" (203.2mm x 203.2mm x 101.6mm)	
	LS-E12	Screw Cover Enclosure	12" x 12" x 4" (304.8mm x 304.8mm x 101.6mm)	

31801r1 Rev 04/2021

	PROJECT		LOCATION/ TYPE		

1